
Scanner Central Admin Agent 1.2
README

Copyright PFU LIMITED 2011 - 2013

This file contains points to note and the latest information not included elsewhere (for example, in the online Help), which you are recommended to read before using this product.
Be sure to read this file prior to use.

Use in High Safety Applications

This product has been designed and manufactured on the assumption that it will be used in office, personal, domestic, regular industrial, and general purpose applications. It has not been designed and manufactured for use in applications that pose a direct danger to life and health when a high degree of safety is required (referred to in this manual as "high-safety applications"), such as in the control of nuclear reactions at nuclear power facilities, automatic flight control of aircraft, air traffic control, operation control in mass-transport systems, medical equipment for sustaining life, and missile firing control in weapons systems, and when provisionally the safety in question is not ensured. The user should use this product while providing measures for ensuring safety in such high-safety applications. PFU LIMITED assumes no liability whatsoever for damages arising from use of this product by the user in high-safety applications, and for any claims or compensation for damages by the user or a third party.

[Contents]

1. Requirements
2. Installation
3. Uninstallation
4. Points to Note

1. Requirements

1.1 Hardware

CPU: Intel(R) Pentium(R) 4 1.8 GHz or higher
(Recommended: Intel(R) Core(TM) i5 2.5 GHz or higher, excluding mobile use)
Memory: 1 GB or more (Recommended: 4 GB or more)
Disk space: 2.2 GB or more of free space
XGA monitor or better
LAN cable
Pointing device (e.g. mouse)

1.2 Software

Operating System

Windows(R) XP Home Edition (Service Pack 3 or later)
Windows(R) XP Professional (Service Pack 3 or later)
Windows(R) XP Professional x64 Edition (Service Pack 2 or later)
Windows Server(R) 2003 R2, Standard Edition (Service Pack 2 or later)
Windows Server(R) 2003 R2, Standard x64 Edition (Service Pack 2 or later)
Windows Vista(R) Home Basic (32/64-bit) (Service Pack 1 or later)
Windows Vista(R) Home Premium (32/64-bit) (Service Pack 1 or later)
Windows Vista(R) Business (32/64-bit) (Service Pack 1 or later)
Windows Vista(R) Enterprise (32/64-bit) (Service Pack 1 or later)
Windows Vista(R) Ultimate (32/64-bit) (Service Pack 1 or later)
Windows Server(R) 2008 Standard (32/64-bit)
Windows Server(R) 2008 R2 Standard (64-bit)
Windows(R) 7 Home Premium (32/64-bit)
Windows(R) 7 Professional (32/64-bit)

Windows(R) 7 Enterprise (32/64-bit)
Windows(R) 7 Ultimate (32/64-bit)
Windows(R) 8 (32/64-bit)
Windows(R) 8 Pro (32/64-bit)
Windows(R) 8 Enterprise (32/64-bit)
Windows(R) 8.1 (32/64-bit)
Windows(R) 8.1 Pro (32/64-bit)
Windows(R) 8.1 Enterprise (32/64-bit)
Windows Server(R) 2012 Standard (64-bit)
Windows Server(R) 2012 R2 Standard (64-bit)

Microsoft(R) .NET Framework
Microsoft(R) .NET Framework 2.0 (Service Pack 2 or later)
Microsoft(R) .NET Framework 3.0 (Service Pack 2 or later)
Microsoft(R) .NET Framework 3.5 (Service Pack 1 or later)

TWAIN driver (including Software Operation Panel)
ISIS driver (including Software Operation Panel)
VRS (including Software Operation Panel)
PaperStream IP (TWAIN) (including Software Operation Panel)
PaperStream IP (TWAIN x64) (including Software Operation Panel)
PaperStream IP (ISIS) (including Software Operation Panel)

Scanner Central Admin Server
Scanner Central Admin Server 4.0 or later

1.3 Image Scanners Supported by Scanner Central Admin

This product supports the following image scanners:

fi-7280/fi-7180/fi-7260/fi-7160
fi-6240Z/fi-6140Z/fi-6230Z/fi-6130Z
fi-6800
fi-5950
fi-6770/fi-6670
fi-6770A/fi-6670A
fi-6750S
fi-5530C2

1.4 The Driver Version of Image Scanners Supported by Scanner Central Admin

This product supports the following driver version of image scanners.

Software Operation Panel needs to be installed together with the driver.

If an old version of the driver or Software Operation Panel is installed, this product may not operate properly or some of the functions may not be available.

Update them before use.

fi-7280/fi-7180/fi-7260/fi-7160
PaperStream IP (TWAIN): 1.1 or later
PaperStream IP (TWAIN x64): 1.1 or later
PaperStream IP (ISIS): 1.1 or later

fi-6240Z/fi-6140Z/fi-6230Z/fi-6130Z
PaperStream IP (TWAIN): 1.0 or later
PaperStream IP (ISIS): 1.0 or later
TWAIN driver: V10.21.310 or later
ISIS driver: 2.1.11211.1002 or later
Kofax VRS: Software VRS 5.1.0265 or later

fi-6800

PaperStream IP (TWAIN): 1.0 or later
PaperStream IP (ISIS): 1.0 or later
TWAIN driver: V10.10.805 or later
ISIS driver: 2.1.11210.4001j or later
Kofax VRS: Hardware VRS 5.1.0265 or later

fi-5950

PaperStream IP (TWAIN): 1.0 or later
PaperStream IP (ISIS): 1.0 or later
TWAIN driver: V10.10.805 or later
ISIS driver: 2.1.11210.9002j or later
Kofax VRS: Hardware VRS 5.1.0265 or later

fi-6770/fi-6670

PaperStream IP (TWAIN): 1.0 or later
PaperStream IP (ISIS): 1.0 or later
TWAIN driver: V9.21.1307 or later
ISIS driver: 2.1.11210.5001 or later
Kofax VRS: Software VRS 5.1.0265 or later

fi-6770A/fi-6670A

TWAIN driver: V9.21.1307 or later
ISIS driver: 2.1.11210.5001 or later
Kofax VRS: Hardware VRS 5.1.0265 or later

fi-6750S

PaperStream IP (TWAIN): 1.0 or later
PaperStream IP (ISIS): 1.0 or later
TWAIN driver: V9.21.1307 or later
ISIS driver: 2.1.11210.5001 or later

fi-5530C2

PaperStream IP (TWAIN): 1.0 or later
PaperStream IP (ISIS): 1.0 or later
TWAIN driver: V9.21.1307 or later
ISIS driver: 2.1.11210.9002s or later
Kofax VRS: Software VRS 5.1.0265 or later

All models

Software Operation Panel : V3.5.20 or later

2. Installation

Log on as a user with Administrator privileges, and then install the program.

Specify a local disk folder as the installation folder.

Do not install directly to a root folder, as operation may not be normal.

Do not use any of the following symbols for the installation folder name, as operation of the program may not be normal.

;, . # %

Easy installation in multiple computers is possible with Automatic Setting/Registration Processing. For more details, refer to Scanner Central Admin User's Guide.

3. Uninstallation

Log on as a user with Administrator privileges, and then uninstall the program.

4. Points to Note

4.1 Points to Note on System Requirements

This software is not guaranteed to run in the following cases:

- Operation with Terminal Services Client or by a client using a Remote Desktop Connection
- Operation in a virtual PC (including Windows XP Mode in Windows 7)
- Operation by multiple users
- Operation by a guest user

4.2 Points to Note Regarding Scanners

(1) The following cautions apply for connection to the VRS Image Processing board.

-Scanner monitoring (error notification) is not supported.
<<Scanner Models: fi-6800, fi-5950, fi-6770A, fi-6670A>>

-Export/import of Software Operation Panel settings is not supported.
<<Scanner Models: fi-5950, fi-6770A, fi-6670A>>

(2) For the following scanners, update of the firmware is only available for scanner versions A1 or later.
<<Scanner Models: fi-5950>>

For firmware updates of scanners with a scanner version of A0, contact your FUJITSU scanner dealer or an authorized FUJITSU scanner service provider.

For the scanner version, check the label on the back of the scanner.

Scanner version: A0

```
+ - + - + - + - + - + - + - + - + - + - + - +
| A | - | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 |
+ - + - + - + - + - + - + - + - + - + - + - +
| | | | | | | | | | | | | |
+ - + - + - + - + - + - + - + - + - + - + - +
```

Scanner version: A1

```
+ - + - + - + - + - + - + - + - + - + - + - +
| A | - | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 |
+ - + - + - + - + - + - + - + - + - + - + - +
| | | | | | | | | | | | | |
+ - + - + - + - + - + - + - + - + - + - + - +
```

(3) Update of firmware (imprinters) is not supported for scanners installed with both the pre-imprinter and the post-imprinter.

<<Scanner Models: fi-5950>>

(4) Export of Software Operation Panel settings is not supported for the following scanners.

<<Scanner Models: fi-5530C2>>

(5) Maintenance parts for which cleaning notification is available are installed on the following scanners:

<<Scanner Models: fi-6800 and fi-5950>>

(6) Cleaning notification by the number of pages scanned is not supported for the following scanners:

<<Scanner Models: fi-6240Z, fi-6140Z, fi-6230Z, fi-6130Z and fi-5530C2>>

(7) Glass cleaning notification is not supported for the following scanners:

<<Scanner Models: fi-6240Z, fi-6140Z, fi-6230Z, fi-6130Z, fi-6800, fi-5950, fi-6770, fi-6670, fi-6770A, fi-6670A, fi-6750S and fi-5530C2>>

=====

Microsoft, Windows, Windows Server, Windows Vista, and SharePoint are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.

ISIS is a registered trademark of EMC Corporation in the United States.

Intel, Pentium, and Intel Core are registered trademarks or trademarks of Intel Corporation in the United States and other countries.

Kofax and VRS are registered trademarks or trademarks of Kofax, Inc.

ScanSnap, ScanSnap Manager, and PaperStream are registered trademarks of PFU LIMITED in Japan.

Other company names and product names are the registered trademarks or trademarks of the respective companies.